

□

Thank you for purchasing *The Pocket Console DMX™*.

Battery Install


The unit comes ready to go with an installed 9v battery, our compliments. If it is dead, then it may have turned ON in transit and you will need to replace it. Our apologies if this is the case. To replace, turn it over, unscrew the four corner screws on the backplate and carefully replace. **BE CAREFUL...IF YOU CHOOSE TO USE JUST THE AC/DC POWER ADAPTER WITHOUT THE BATTERY INSTALLED, BE SURE TO TAPE OVER THE TERMINALS SO AS NOT TO CAUSE A SHORT CIRCUIT TO THE MOTHERBOARD FROM THE BATTERY LEADS.** We recommend keeping a new battery in the unit at all times or regardless of charge, unless the battery is too old and leaks, of course. Also, be very careful with the backplate and the DATA cord during this procedure. The Battery lives in a clip on the backplate.

Patch

Turn the unit ON. Switch into PATCH mode. Display will read Dimmer 001. Using the NEXT or LAST buttons, choose the dimmer you wish to patch. Press one of the chosen BUMP buttons under a slider and you have now patched that dimmer to that slider. Continue the process as much as you like. All 512 dimmers could go to one slider, if you choose. Also, **holding down** the NEXT or LAST button will stream through the dimmers. Holding down UNPATCH or holding down a BUMP button simultaneously, will PATCH or UNPATCH thru all selected dimmers as long as you hold down the buttons.

When in PATCH mode, the LED under the slider will only light if the selected dimmer is patched to that slider. This is all the LED indicators are for. **THEY ARE NOT SLIDER LEVEL OR BUMP INDICATORS.**

When in PATCH mode, the unit will still send DMX and the changes will be instantaneous if you have sliders up on the panel. Holding down the NEXT or LAST buttons will stream through the dimmers slowly at first and then **VERY QUICKLY**, just like on an LED based alarm clock.



Operation

Switch to NORMAL. The patch display will go dark. This is to save battery life. There will be a light glowing LED in the lower right corner of the display to indicate battery life "good." (If this light is blinking, time for a new battery.) Plug the DATA plug into the DMX device you are operating and away you go. If things aren't working, make sure you are patched properly. Also, in this NORMAL mode, the BUMP buttons are true bump buttons, but the LED does not indicate a flash, FYI.

Specifications

Dimensions: 6-5/8" wide x 3-1/4" tall x 1-3/8" deep
(1-5/8" for fader handle clearance)

DMX cable length with connector - 18" min.

Weight with battery - 13oz

Shipping weight - 1lb, 14oz

Packaged size : (Pocket Console DMX™, AC adapter and instructions)
10.5" X 8" X 2-1/4"

9 Volt Alkaline Battery Life - 3 hours minimum

120v AC adapter

Number of DMX dimmer addresses supported - 512

Number of Faders - 8 with bump buttons

Data output - DMX-512 1990 standard

DMX Update Speed: 44hz

Made in USA! - by BC Illuminations, San Antonio, Texas

THANK YOU!

WARRANTY

The Pocket Console DMX™ is guaranteed for 90 Days from date of delivery. Please return ASAP after you have any problems and we will take care of it. Dead or leaking batteries, abnormal wear and tear, abuse, or "Pepsi Syndrome" are not covered under this warranty. Software crashes and faulty hardware are. But this should not happen. Enjoy!